

## **Mikas Middle East FZE**

Office No: 139/A, Building -Q1-04 **Sharjah Airport International Freezone** PO Box: 61397, Sharjah **United Arab Emirates.** 

Machinery for Industrial Kinetics, Access, and Services

mikas.ae

## 150 KVA 50 Hz **3 PHASE**

# **Perkins**

GENERATING SET MODEL ( UPSP 150 )			
Output Ratings	Prime	Standby	
380-415 V, 3 ph, 50 Hz, 1500 rpm	150 KVA	165 KVA	
	120 KW	132 KW	
380-415 V, 3 ph, 60 Hz, 1800 rpm	169 KVA	188 KVA	
	135 KW	150KW	

### **ENGINE / TECHNICAL DATA**

Ratings at 0.8 Power Factor

Engine Make	Pe	Perkins		
Engine Model	1106A-	70TAG2		
Governing Type	Elec	Electrical		
Number of Cylinders	26	6		
Cylinder Arrangement	Vertic	cal in line		
Bore and Stroke mm	10:	105 x 135		
Displacement / Cubic Capacity litres		7.01		
Induction System	Turbocharged, a	Turbocharged, air to air aftercooled		
Cycle	4 stroke			
Combustion System	Direct Injection			
Compression Ratio	16:1			
Rotation	Anti-clockwise, viewed on flywheel			
Cooling System	Water - cooled			
Frequency and Engine Speed	50Hz & 1500rpm	60Hz & 1800rpm		
	8			
Gross Engine Power kW (hp)	136.8 (183.4)	150.5 (201.7)		
Fuel Consumption @ 50% load L/hr	16.5	19.4		
@ 75% load L/hr	24.1	28.9		
@ 100% load L/hr	31.5	37.6		
Total Lubrication System Capacity litres	16.5	16.5		
Total Coolant Capacity (inc. radiator) litres	21	21		
Exhaust Temperature: °C	580	595		
-				

Image for illustrative purposes only



170KVA

3 PHASE

LTERN		

Make	UF	PS / Leroy Somer
Model	UPS274E	/ LSA (TAL)44 J
No. of bearin	gs	1
Insulation cl	ass	Н
Wires		6/12
Ingress Prote	ection	IP23
<b>Excitation Sy</b>	/stem	Shunt
Winding Pito	h	2/3

uverspeea		2250 mn '
Voltage Regulation (steady)		± 1%
CONTROL PANEL		
•	_	0

Make Deep Sea 4000 SERIES Model

The DSE 4000 Series is an Auto Start ControlModule for single genset applications. It includes a backlit LCD display which clearly shows the status of the engine all the times. This module can either be programmed using the front panel or by using the DSE configuration suite PC software.

#### Metering and Alarm indications:

- Generator frequency
- Underspeed, Overspeed
- Generator volts (L-L, L-N)
- Generator current
- Engine oil pressure
- · Engine coolant temperature
- · Hours run counter
- · Battery volts
- Fail to start/stop
- · Emergency stop
- · Failed to reach loading voltage/frequency
- · Charge fail
- · Low DC voltage
- · CAN diagnostics and CAN fail/error









#### 1. ENGINE

Perkins four stroke heavy duty high performance industrial type diesel engine.

50 Hz

#### 2. ENGINE FILTRATION SYSTEM

- Cartridge type dry air filter.
- Two Cartridge type fuel filters.
- Full flow lube oil filter.

All filters have replaceable elements.

#### 3. COOLING RADIATOR

Radiator and cooling fan, complete with safety guards, designed to cool the engine at high ambient temperatures (consult your dealer for de-ration factors)

#### 4. EXHAUST SYSTEM

Exhaust gas flow Maximum allowable back pressure

31.3 (m^3/min 18.0 (kPa)

## 5. CIRCUT BREAKER TYPE

3 pole MCCB. (4 pole is optional)

#### 6. FUEL SYSTEM

The baseframe design is incorporated with an integral fuel tank with a capacity of approx. 8 hours running at Full Load. The tank is supplied complete with fill cap breather, fuel feed and return lines to the Engine and drain plug.

#### 7. ALTERNATOR

#### 7.1 INSULATION SYSTEM

- The insulation system is Class H.
- All windings are impregnated in either a triple dip thermosetting liquid, oil and acid resisting polyester varnish or vacuum pressure impregnated with a special polyester resin.
- Heavy coat of antitracking varnish additional protection against moisture or condensation.

#### 7.2 AUTOMATIC VOLTAGE REGULATOR (AVR)

The fully sealed Automatic Voltage Regulator maintains the Voltage Regulation at ±1%. Nominal adjustment by means of a trim pot incorporated on

## MOUNTING ARRANGEMENT

The Engine and Alternator are directly coupled by means of an SAE flange. The Engine flywheel is flexibly coupled to the Alternator rotor.

#### 8.2 ANTI-VIBRATION MOUNTING PADS

Anti-Vibration pads are affixed between the Engine / Alternator feet and the Baseframe thus ensuring complete vibration isolation of the rotating assembly.

#### 8.3 SAFETY GUARDS

The Fan & Fan Drive along with the Battery Charging Alternator are Safety Guard protected for personnel protection.

## 9. FACTORY TEST

- The Generating set is load tested before dispatch
- All protective devices control functions and site load conditions are simulated. The generator and it's systems are checked before dispatch.

#### 10. EQUIPMENT FINISHING

All mild steel components are fully degreased and painted with powder coated paint to ensure maximum scuff resistance and durability.

#### 11. DOCUMENTATION

Operation & Maintenance manual, Circuit wiring diagrams and Commissioning / Fault Finding instruction leaflets are accompanied with the Generator.

#### 12. QUALITY STANDARDS

equipment meets the following standards: BS4999, BS5000, BS5514 IEC 60034, VDE0530, NEMA MG 1.22 and ISO 8528.

#### WARRANTY


All of the Generating Sets are covered under a warranty policy for a period of 12 months or 1000 working hours, Warranty of the equipment is in line with manufacturers warranty terms & conditions. ment for more details, as it may vary for different countries)


In line with continuous product development, we reserve the right to change specifications without notice.

## STANDARD GENERATOR DIMENSION AND WEIGHT

## Silent Type (with Soundproof Canopy)







Open

